



R. Den Hartog, J.K.Wigmore, G.Brammertz, A.Peacock, D.Martin, P.Verhoeve, N.Rando

The effect of quasiparticle selfgeneration on the performance of small gap multiple tunnelling STJs



STJs as photon detectors

Current trend:

- a. small gap (better resolution)
- b. high responsivity (thin homogeneous barriers, low losses)

Modelling:

Rothwarf-Taylor scheme (RT-model)

Statement:

For thin barriers with $\rho < 10 \mu \Omega \cdot cm^2$

RT model is completely inadequate for the analysis of quasiparticle and phonon dynamics for all traditional superconductors except for unproximised Nb

Energy gain in sequential cycles of direct- and back-tunnelling events



- a. Direct tunnelling $1 \rightarrow 2$,
 - followed by relaxation $2 \rightarrow 3$
- b. Back-tunnelling 3 -> 4

from relaxed state 3

c. Sequential direct- back-

tunnelling cycle 1 \rightarrow 2 \rightarrow 3 \rightarrow 4

with intermediate relaxation

d. Sequential direct- back-

tunnelling cycle $1 \rightarrow 2 \rightarrow 5$ without relaxation



Tunnelling and electron-phonon interaction processes in the STJ





Spectral balance equations

 $-\frac{P_m}{\tau_m} + \sum_{s=m+1}^{\infty} \frac{P_s}{\tau_{s\to m}}$ $P_m - P_m^0$ $\tau_{l,m}$ $-\Gamma_{m\to m+\nu}P_m+\Gamma_{m+\nu\to m}P_{m+\nu}$ $-\Gamma_{m\to m-\nu}\boldsymbol{P}_m+\Gamma_{m-\nu\to m}\boldsymbol{P}_{m-\nu}$ $-2N_{0}\sum_{s=0}^{\infty}R_{m,s}^{*}(P_{m}P_{s}-P_{m}^{0}P_{s}^{0})$ $+\sum_{s=0}^{\infty}\frac{1}{\tau_{m,s}}(P_s\rho_m-P_m\rho_s)N(|m-s|\delta)$ $+\sum_{s=s}^{\infty}\frac{P_s}{\tau}$

QP transitions in and out with spontaneous phonon emission

QP losses other than recombination

Direct tunnelling and cancellation Back-tunnelling and cancellation

OP recombination

QP transitions due to absorption and stimulated emission of non-equilibrium phonons (mostly sub-gap phonons) QP generation

AI STJ



Quasiparticle and phonon distribution functions



Phonon distribution "supported" by 1 calculated QP distribution at eVb=1/3. 1. thermal; 2-6 – different coupling to bath.



QP distribution functions:

eV_b=1/2; 2. eVb=1/3; 3. at thermal equilibrium; 4. "equilibrium" with
the same QP density.



Current voltage characteristics





Calculated I-V curves: 1. no loss; 2-5 with loss times 500, 120, 110 and 100 microseconds respectively $T_0 = 100 \text{mK}$ Measured I-V curves: 1. T0 =350mK; 2. T0 =150mK; 3. T0 =130mK ; 4. T0 =100mK; 5. T0 =40mK KJL275: 100nm Ta/265nm Al/AlOx/265nm Al/100nm Ta



Current voltage characteristics



Calculated I-V curves: a. no loss; b-e with loss times 500, 120, 110 and 100 microseconds respectively T0 =100mK

Measured I-V curves: 1. T0 =350mK; 2. T0 =150mK; 3. T0 =130mK ; 4. T0 =100mK; 5. T0 =40mK KJL275: 100nm Ta/265nm Al/AlOx/265nm Al/100nm Ta



Kozorezov Temporal evolution of the QP distributions in the biased STJ



Vb=34microvolts Initially monochromatic distribution below the Active region threshold





Vb=34microvolts Initially monochromatic Vb=235 microvolts distribution at the edge

KJL275 Self-generation not included



Summary

- We have presented evidence, both theoretical and experimental, for the existence of a new non-equilibrium qp state in low gap, low loss STJs;
- The formation of broad non-monotonic spectral distribution of QPs invalidates classical RT model;
- We derived a set of spectral balance equations from the system of kinetic equations for interacting QPs and phonons in superconductors
- Even in the absence of QP self-generation the STJ responsivity and signal decay times and their variation with bias voltage and bath temperature strongly depend on details of QP and phonon distribution